

CH1000 Security Communications System

Simple Installation & Operation
Distributed Architecture
5 Year Warranty
RJ45 Terminations, CAT5 Wiring
Remote Access via LAN, WAN
256 Audio Points
64 Multipurpose Zones
32 Call in Groups
Up To 128 UTP Cameras
Up to 8 DA1/Standard Phone/PBX
Ports
Up to 2 Intercom Channels
2 Program Inputs
262 Inputs/6 Outputs
25 Built in Tones
Add up to 25 More WAV Files for
Tones
Microphone Input
Ethernet Port
Class D Amplification
Integrated Master Clock
Unlimited Events
Unlimited Schedules



The CareHawk CH1000 Communication System simplifies installation, programming and daily operation. Visual menus and operator prompts ease operation. Training new operators takes minutes not days. Schedules can be set in advance, at one time for the year. Make changes securely and remotely, even from your home PC!

Installation requires only 1/3rd the wire of other systems. Fewer wires and components dramatically increase reliability. Schedule bells, pre-recorded announcements, background music, cameras, security sensors inputs, and outputs.

The CH1000 is a fully scalable and field upgradable system. All future system features and enhancements are backward compatible.

Power: 120 VAC, 3.5A
Weight: 30 lbs

Finish: Powder Coat Paint

Mounting: Wall Mount 4 Screws, Rack Mount Available

Dimensions: 18.5 inch X 17 Inch X 5.5 Inch

USA & CANADA

Toll Free: 1 (888) 223-5816

Fax: (519) 743-8883 | Email: info@carehawk.com

CH1000 Security Communications System

8 Line x 20 character backlit menu driven Administrative Console



Sync secondary clocks via the built in Master Clock and the unlimited schedules & events



Distributed technology allows for 1 CAT5 home run for every 16/32 ports



Simultaneously connect call in switches, motion sensors, cameras, and speakers on every port



Utilize low cost UTP cameras

USA & CANADA

Toll Free: 1 (888) 223-5816

Fax: (519) 743-8883 | Email: info@carehawk.com